

Max. egeneffekt i LK's tavlekomponenter

Tavlekomponent	Max. egeneffekt		Tavlekomponenter	Max. egeneffekt		Tavlekomponent	Max. egeneffekt
Fejlstrømsafbryder PFI:			Automatsikringer			IHC komponenter:	
4 pol	40A	12,8W	1 pol + N (36 mm)	6A	4,8W	Strømforsyning 72 W (108 mm)	12W
4 pol	63A	12,8W		10A	2,8W	Strømforsyning 15W (72 mm)	6,7W
Fejlstrømsafbryder HPFI:				13A	4,6W	Dimmer 350 LR (36mm)	5W
2 pol	40A	6,4W				Dimmer 350 CR (36 mm)	5W
4 pol	40A	12,8W				Dimmer 300 UNI (36 mm)	5W
4 pol	63A	12,8W				Dimmer 600 CR (108 mm)	12W
			3 pol + N (72 mm)	10A	5,5W	Dimmer 1000 LR (108 mm)	15W
Gruppeafbrydere GA 1:				13A	6,9W	Outputmodul 230 V (72mm)	7,2W
1 pol (18 mm)	6A	1,0W		16A	7,7W	Outputmodul 400/8x10 (108 mm)	9,6W
				20A	8,8W		
	10A	1,6W				Outputmodul 400/8x16 (108 mm)	14W
	13A	2,4W	Lastafbryder			Outputmodul 24 V (72 mm)	8,3W
	16A	2,3W	1 pol (18 mm)	20A	0,5W	Outputmodul 1 - 10V (72 mm)	4,5W
1 pol + N (36 mm)	6A	1,1W	4 pol (36 mm)	32A	3,0W	Inputmodul 230 V (72 mm)	2,5W
			4 pol (72 mm)	63A	6,0W		
	10A	1,8W				Inputmodul 24 V / 24 mA (72 mm)	9,4W
	13A	2,7W	Kontaktor 4 pol			Inputmodul 24 V / 3 mA (72 mm)	1,1W
	16A	2,7W	Sikringsholder D02 (81 mm)			Controller (144 mm)	2W
3 pol (54 mm)	6A	3,3W	Lysdæmper DM-18 (18 mm)			Controller Viewer (108 mm)	3,5W
	10A	5,1W	Stikledningsklemme			Voice Modem (72 mm)	1,6W
	13A	7,5W	Termostat (36 mm)			Alarm Backup (36 mm)	2,1W
	16A	7,2W	PIR-kontrolenhed (36mm)				
3 pol + N (72 mm)	6A	3,4W					
	10A	5,3W					
	13A	7,8W					
	16A	7,6W					
						LK NETLON:	
						Controller	2,0W
						Relæboks 4 relæer	NO 2,25W
						Relæboks 8 relæer	NO 4,5W
						Relæboks 8 relæer	NC 7,8W